

HN-A500I

I Power Amplifier

HN-A500I is a high efficient 500W Power/Booster amplifier provides audio signal amplification for public address and voice alarm system, It is reliable, efficient and light in weight.



FEATURES AND BENEFIT



**100V & 4-16 OHMS
TRANSFORMER-
LESS DESIGN**



**SUPER CLASS-D TOPOLOGY
FULL BAND WITH
PWM MODULATOR**

- Ultra low distortion



**LED STATUS
INDICATIONS**



**OUTPUT SHORT-CIRCUIT
AND THERMAL PROTECTION**

TECHNICAL SPECIFICATIONS

ELECTRICAL	
Mains power supply	180~250 Volts AC 50 Hz
Power Requirement	700 VA
Amplifier topology	Class D >90% efficiency
Frequency response	70 Hz to 20 KHz
THD + N @ 1 KHz	0.1%
Signal input / Output	Balanced Line in (RJ45) - LineOut 100 V signal input - Phoenix
SNR (dB)	102
Dynamic range	93dB
Power Output	500 watts 100 Volt speaker output - Phoenix connector
Damping factor @ 8 Ohm	300
Protection	Output Short-circuit Thermal shut-down
Dimension (mm)	95.2 H x 431.8 W x 304.8 D
Operating Temperature & Humidity	-10°C to 50°C @ 90% relative humidity (non condensing)
Cooling	Forced Air cooling with Fan
Weight	5.25 Kg
Certifications	CE Complied

For more information,

www.honeywellbuildings.in

Call: 000-8000-502167

Email: HBT-IndiaBuildings@Honeywell.com

Honeywell HBT India Buildings

Unitech Trade Center, 5th Floor, Sector-43,

Block C, Sushant Lok Phase - I,

Gurgaon - 122 002.

HN - IA500 | 01 | 09/21
© 2021 Honeywell International Inc.

**THE
FUTURE
IS
WHAT
WE
MAKE IT**

Honeywell